



AP 1001 Sensor (10 Gbps)

Visibility made simply elegant

The Corelight AP 1001 Sensor gives your SOC comprehensive, actionable insights into your network with high-fidelity, structured data.

Plug-and-play, configure in 15 minutes

Corelight Sensors are zero maintenance and take only minutes to deploy: connect the traffic feed, specify where to send logs and extracted files, and you're done. Get new features via automatic updates and enterprise support from Zeek's creators.

Tuned for enterprise performance and scale

Engineered from the ground up with keen attention to detail, Corelight Sensors are security-hardened and run a custom OS based on the Linux kernel. A specialized NIC provides the performance that large-scale deployments require, with built-in support for merging high-volume traffic feeds.

The features you wish open-source Zeek had

Corelight has merged the power of Zeek with a suite of enterprise features that dramatically improve Zeek usability, like an intuitive management UI, sensor health metrics, fleet management, and automated data export to Splunk, Elastic, Kafka, Syslog, S3, and more.

Best-in-class Zeek and Suricata deployment in a compact 1U sensor:

- Engineered for stability and performance, by the creators of Zeek
- Four 1G/10G SFP/SFP+ interfaces in a powerful, specialized NIC
- Intuitive, 15-minute configuration, with a beautiful web app UI
- Data export to Kafka, Splunk, Elastic Search, SIEMs, syslog, Amazon Kinesis, Apache Avro, and SFTP
- High performance and efficient file extraction
- Comprehensive REST API for configuration and monitoring
- Minimalist, custom OS optimized for secure operation
- Automatic updates and feature enhancements

AP 1001 Sensor (10 Gbps): Specifications

- World-class support from the definitive Zeek experts included, additional [support programs](#) available
- For more info on Suricata support in the AP 1001 Sensor, read [this whitepaper](#)

Specifications

Size and weight	1U rackmount, (19 x 25.6 x 1.75 inches), 40 lbs
Monitoring interface	Four 1G/10G SFP/SFP+ modules. Support for copper and optical modules at 1G and 10G
Management interface	One 10/100/1000 copper ethernet port Two 1/10G SFP+ ports
External connector	VGA, USB
Power	120/240 VAC 50/60 Hz redundant dual PSUs. 700W at 110V or 750W at 220V. Approximately 180W usage when idle and 290W usage at load
Operational mode	Out of band—fed by tap, span, or packet broker



Defenders have always sought the high ground in order to see farther and turn back attacks. Corelight delivers a commanding view of your network so you can outsmart and outlast adversaries. We capture, interpret, and connect the data that means everything to defenders.

info@corelight.com | 888-547-9497